

# ZMD-DR-SFN6

## View 16 Channels Remotely with the ZMD-DR-SFN6

### View 16 Channels Remotely

## ZMD-DR-SFN6

## Firmware Update

Warning do not use this if you are running on a Mac! This firmware will make the DVR no longer work with your Apple Computer!

1. Download the file located below:  
[http://files.zmodo.com/Firmwares/DVRs/SFN6/SFN6\\_Update.zip](http://files.zmodo.com/Firmwares/DVRs/SFN6/SFN6_Update.zip)
2. Open the folder containing the downloaded SFN6-Firmware-Update
3. Right click on the SFN6-Firmware-Update folder and select Extract All
4. Select, Browse, Desktop, Make New Folder
5. Name the folder SFN6-Firmware-Update, select OK
6. Select Extract
7. Open the SFN6-Firmware-Update folder on the desktop
8. Copy the three files onto an empty USB drive
9. Power OFF the ZMD-DR-SFN6
10. Plug the USB drive into one of the two USB ports on the front panel of the ZMD-DR-SFN6

# ZMD-DR-SFN6

11. Power ON the ZMD-DR-SFN6
12. The ZMD-DR-SFN6 will update, do NOT unplug the USB drive or power off the DVR
13. Open the folder containing the downloaded ActiveX Reset Script
14. Select, Browse, Desktop, Make New Folder
15. Name the folder ActiveX Reset Script, select OK
16. Select Extract
17. Open the ActiveX Reset Script folder on the desktop
18. Right Click on Erase\_IE\_Control\_V0.2 and select Run as administrator
19. When prompted press any key and wait for the scan to finish
20. Open IE, Firefox, or Chrome and log into the DVR

After the firmware update, in order to view from the desktop application again, you will need to uninstall the old version of NetDVR and install the version located here: <https://dl.dropbox.com/u/72446397/NetDvr.msi>

Unique solution ID: #1019  
Author: Patricia Pyle  
Last update: 2013-08-26 17:40