

# ZMD-DT-SCN4

## Resolution reset for DT-SCN DVR systems

**\*\*\*\*If the system is networked, you can reset resolution from the PC\*\*\*\***

Power off the system first then

Restart the DVR and wait 1 minute for before executing the following commands.

Menu

Right (2 times)

Menu wait 5 seconds

Menu

Down (2 times)

Right

Up (1-4 times depending on how high the resolution was set)

Right

Down (5 times)

Right (2 times)

wait for 5 seconds and hit meue

If screen doesn't show up please power unit down and power back up and repeat the following steps.

If the above procedure was input correctly the DVR will restart itself.

Unique solution ID: #1350

Author: Jamie Alksnis

Last update: 2015-03-24 11:56